

Configuration Guide



P.O. Box 280
Necedah, WI 54646 USA
1-800-356-5794
www.bestpower.com

Section 1	Select One	kVA	Slots	Pwr Mod.
Select your current power requirements.	<input type="radio"/>	3kVA	1	1
	<input type="radio"/>	6kVA	2	2
	<input type="radio"/>	9kVA	3	3
	<input type="radio"/>	12kVA	4	4
	<input type="radio"/>	15kVA	5	5
	<input type="radio"/>	18kVA	6	6

Section 2	Select One	kVA	Slots	Pwr Mod.
Select your additional future power requirements. (1)	<input type="radio"/>	None	0	0
	<input type="radio"/>	3kVA	1	1
	<input type="radio"/>	6kVA	2	2
	<input type="radio"/>	9kVA	3	3
	<input type="radio"/>	12kVA	4	4
	<input type="radio"/>	15kVA	5	5

Section 3	Select One	kVA	Slots	Pwr Mod.	N+X
Select a level of desired redundancy.	<input type="radio"/>	None	0	0	None
	<input type="radio"/>	3kVA	1	1	N+1
	<input type="radio"/>	6kVA	2	2	N+2
	<input type="radio"/>	9kVA	3	3	N+3
	<input type="radio"/>	12kVA	4	4	N+4
	<input type="radio"/>	15kVA	5	5	N+5

3a. Total Power Modules

Section 4	Select One	Slots	Bat Mod.	Required kVA						
				3	6	9	12	15	18	
Select runtime per battery module (2 per string). Note: Shaded area requires external battery options. Runtimes shown below line utilize N+X power modules or an auxiliary charger.	<input type="radio"/>	1	2	8						
	<input type="radio"/>	2	4	24	8					
	<input type="radio"/>	3	6	43	16	8				
	<input type="radio"/>	4	8	58	24	13	8			
	<input type="radio"/>	5	10	80	32	18	13	8		
	<input type="radio"/>	6	12	95	40	24	16	11	8	
	<input type="radio"/>	7	14	119	49	29	19	14	11	
	<input type="radio"/>	8	16	135	58	35	24	18	13	
	<input type="radio"/>	9	18	155	69	40	29	20	15	
	<input type="radio"/>	10	20	165	83	46	33	24	18	
	<input type="radio"/>	11	22	200	90	54	36	28	20	
	<input type="radio"/>	12	24	215	103	58	41	31	24	
	<input type="radio"/>	13	30	225	113	63	47	34	27	
	<input type="radio"/>	14	36	245	123	73	52	38	31	
	<input type="radio"/>	15	42	270	135	80	56	41	34	
	<input type="radio"/>	16	48	290	143	86	58	44	36	
	<input type="radio"/>	17	54	315	148	93	65	46	38	
	<input type="radio"/>	18	60	335	156	100	70	51	41	
	<input type="radio"/>	19	66	350	165	107	75	56	44	
	<input type="radio"/>	20	72	365	175	115	80	58	45	
	<input type="radio"/>	22	78	395	190	125	90	66	54	
	<input type="radio"/>	24	84	450	205	143	100	73	58	

4a. Total Battery Modules

4b. Total Slots (2)

Power Module + Battery Module Slots

Section 5	Select One	Type	Vinput and Voutput
Select Power Module	<input type="radio"/>	Universal Power Module	208V, 220V, 230V, 240V
	<input type="radio"/>	Split-phase Power Module	100/200V, 120/208V, 110/220V, 127/220V, 120/240V

Section 6	Modules	Part #	List Price	Modules Total Price (List x total # of Modules)
Calculate Price	Universal Power Module	ASY-0528	\$1,609	\$-
	Split-phase Power Module	ASY-0567	\$1,689	\$-
	Battery Module	ASY-0529	\$169	\$-

Section 7	Basic Enclosure Description	Part#	List Price
Select one based on number of slots required. (3)	<input type="radio"/> 3-slot, 3kVA maximum rating, hardwire termination	0650C030AAAAAAA0	\$709
	<input type="radio"/> 6-slot, 9kVA maximum rating, hardwire termination	0650C060AAAAAAA0	\$1,129
	<input type="radio"/> 9-slot, 18kVA maximum rating, hardwire termination	0650C090AAAAAAA0	\$1,489
	<input type="radio"/> 12-slot, 18kVA maximum rating, hardwire termination	0650C120AAAAAAA0	\$1,739

Section 8	Description	P/N	List Price
Other options, select if required.	<input type="radio"/> Rackmount (3- or 6-slot only)	ASY-0547	\$79
	<input type="radio"/> Caster Option (3- or 6-slot towers only)	ASY-0527	\$59
	<input type="radio"/> 6-slot external battery enclosure	ASY-0541	\$649
	<input type="radio"/> 9-slot external battery enclosure	ASY-0542	\$939
	<input type="radio"/> 12-slot external battery enclosure	ASY-0565	\$1,139

(1) Section 1 + 2 maximum total kVA is 18kVA.
 (2) If total slots are greater than 12, an external battery cabinet must be used.
 (3) Line-cords and receptacles available upon request.

Total