

Power

Pinnacle Plus Tower Runtime Chart



Pinnacle Plus 1500T

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	150	105	1:19	13:17	22:12
20%	300	210	0:49	7:17	12:24
30%	450	315	0:35	4:09	7:40
40%	600	420	0:27	2:52	6:15
50%	750	525	0:21	2:17	4:51
60%	900	630	0:17	1:48	3:54
70%	1050	735	0:14	1:28	3:11
80%	1200	840	0:12	1:18	2:30
90%	1350	945	0:10	1:05	2:18
100%	1500	1050	0:09	1:01	2:14

Pinnacle Plus 700T

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	70	49	2:05	15:16	33:17
20%	140	98	1:16	9:09	18:19
30%	210	147	0:52	6:01	10:35
40%	280	196	0:38	4:10	7:20
50%	350	245	0:28	3:33	6:12
60%	420	294	0:21	2:50	5:09
70%	490	343	0:16	2:15	4:12
80%	560	392	0:13	2:00	3:19
90%	630	441	0:11	1:44	3:00
100%	700	490	0:10	1:39	2:54

Pinnacle Plus 2000T

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	200	140	2:07	11:07	17:47
20%	400	280	1:18	6:09	10:15
30%	600	420	0:55	3:36	6:31
40%	800	560	0:38	2:30	4:35
50%	1000	700	0:28	1:55	3:37
60%	1200	840	0:21	1:32	2:54
70%	1400	980	0:17	1:17	2:25
80%	1600	1120	0:13	1:07	2:09
90%	1800	1260	0:11	0:57	1:50
100%	2000	1400	0:10	0:53	1:44

Pinnacle Plus 1000T

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	100	70	2:04	17:45	37:45
20%	200	140	1:18	10:14	21:15
30%	300	210	0:55	6:33	12:38
40%	400	280	0:38	4:39	8:00
50%	500	350	0:28	3:54	6:29
60%	600	420	0:21	3:03	5:34
70%	700	490	0:17	2:23	5:00
80%	800	560	0:13	2:09	4:29
90%	900	630	0:11	1:50	3:40
100%	1000	700	0:10	1:43	3:24

Pinnacle Plus 3000T

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	300	210	1:20	8:11	13:19
20%	600	420	0:50	4:17	7:15
30%	900	630	0:37	2:11	4:05
40%	1200	840	0:27	1:29	2:49
50%	1500	1050	0:21	1:13	2:16
60%	1800	1260	0:17	0:59	1:49
70%	2100	1470	0:13	0:47	1:29
80%	2400	1680	0:11	0:40	1:20
90%	2700	1890	0:10	0:33	1:07
100%	3000	2100	0:09	0:30	1:03

Power

Pinnacle Plus Rackmount Runtime Chart



Pinnacle Plus 1500RM

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	150	105	1:20	13:20	22:13
20%	300	210	0:50	7:18	12:24
30%	450	315	0:37	4:10	7:40
40%	600	420	0:27	2:54	6:15
50%	750	525	0:21	2:17	4:53
60%	900	630	0:17	1:49	3:55
70%	1050	735	0:13	1:29	3:11
80%	1200	840	0:11	1:18	2:30
90%	1350	945	0:10	1:06	2:19
100%	1500	1050	0:09	1:02	2:15

Pinnacle Plus 700RM

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	70	49	2:07	15:33	33:20
20%	140	98	1:18	9:09	18:20
30%	210	147	0:55	6:01	10:35
40%	280	196	0:38	4:10	7:20
50%	350	245	0:28	3:33	6:13
60%	420	294	0:21	2:49	5:10
70%	490	343	0:17	2:14	4:13
80%	560	392	0:14	2:00	3:20
90%	630	441	0:11	1:44	3:01
100%	700	490	0:10	1:38	2:55

Pinnacle Plus 2000RM

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	200	140	2:01	11:07	17:43
20%	400	280	1:15	6:10	10:14
30%	600	420	0:53	3:38	6:31
40%	800	560	0:35	2:30	4:35
50%	1000	700	0:27	1:56	3:39
60%	1200	840	0:21	1:33	2:55
70%	1400	980	0:16	1:17	2:25
80%	1600	1120	0:13	1:07	2:10
90%	1800	1260	0:11	0:58	1:51
100%	2000	1400	0:09	0:55	1:45

Pinnacle Plus 1000RM

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	100	70	2:04	17:47	37:47
20%	200	140	1:16	10:15	21:15
30%	300	210	0:53	6:33	12:38
40%	400	280	0:37	4:40	8:00
50%	500	350	0:27	3:55	6:30
60%	600	420	0:20	3:04	5:35
70%	700	490	0:16	2:24	5:00
80%	800	560	0:13	2:10	4:30
90%	900	630	0:11	1:51	3:41
100%	1000	700	0:10	1:44	3:24

Pinnacle Plus 3000RM

Load Level	Output Load (VA)	Output Load (Watt)	Internal Runtime (hh:mm)	+ 1 Battery Pack (hh:mm)	+ 2 Battery Pack (hh:mm)
10%	300	210	1:17	8:13	13:20
20%	600	420	0:48	4:18	7:15
30%	900	630	0:35	2:11	4:05
40%	1200	840	0:25	1:30	2:50
50%	1500	1050	0:19	1:14	2:16
60%	1800	1260	0:15	0:59	1:49
70%	2100	1470	0:12	0:48	1:30
80%	2400	1680	0:11	0:40	1:20
90%	2700	1890	0:10	0:33	1:08
100%	3000	2100	0:09	0:31	1:04